SYC SEMICONDUCTORES Y COMPONENTES


LED SPECIFICATION

ATTENTION
OBSERVE PRECAUTIONS FOR HANDLING ELECTROSTATIC DISCHARGE SENSITIVE DEVICES

LED-010-75039

➢ Features

- Single color
- High bright output
- Low power consumption
- High reliability and long life



1. All dimensions are millimeters
2. Tolerance is +/-0.25mm unless otherwise noted


➢ Descriptions：

- Dice material：InGaN
- Emitting Color：

  Super Bright White
- Device Outline：

  ϕ5mm Round Type/ 5mm
- Lens Type： Milky Diffused

➢ Directivity：



LED SPECIFICATION

Absolute maximum ratings（Ta = 25℃）

Parameter	Symbol	Test Condition	Value		Unit
			Min.	Max.	
Reverse Voltage	V_R	I_R = 30μA	5	--	V
Forward Current	I_F	----	----	30	mA
Power Dissipation	Pd	----	----	108	mW
Pulse Current	Ipeak	Duty=0.1mS，1kHz	----	100	mA
Operating Temperature	Topr	----	-20	+85	℃
Storage Temperature	Tstr	----	-25	+100	℃

Electrical and optical characteristics （Ta = 25℃）

Parameter	Symbol	Test Condition	Value			Unit
			Min.	Typ.	Max.	
Forward Voltage	V_F	I_F = 20mA		V8~V10		
Reverse Current	I_R	V_R = 5V	----	----	30	μA
Dominate Wavelength	λ_d	I_F = 20mA		WA~ WD		
Luminous Intensity	I_V	I_F = 20mA		T,U		
Viewing Angle	$2\theta_{1/2}$	I_F = 20mA	60		70	Deg.


BIN ranking for LEDs

BRIGHTNESS BIN

Bin Code	IV(mcd)	Bin Code	IV(mcd)	Bin Code	IV(mcd)	Bin Code	IV(mcd)
A	0-5.0	H	37.2-52.0	Q	390-550	X	4180--5860
B	5.0-7.0	J	52.0-72.8	R	550-770	Y	5860-8200
C	7.0-9.8	K	72.8-102	S	770-1100	Z1	8-10cd
D	9.8-13.7	L	102-145	T	1100-1520	Z2	10-12cd
E	13.7-19.0	M	145-200	U	1520-2130	Z3	12-14cd
F	19.0-26.6	N	200-280	V	2130-3000	Z4	14-16cd
G	26.6-37.2	P	280-390	W	3000-4180	Z5	16-18cd

FOR WHITE COLOR BINS SEE PAGE 3B

PLACING OF WHITE COLOR BINS ON CIE TABLE




FORWARD VOLTAGE (VF) BIN

Bin Code	VF (V)	Bin Code	VF (V)	Bin Code	VF (V)	Bin Code	VF (V)
V1	1.6-1.8	V5	2.4-2.6	V9	3.2-3.4	V13	4.0-4.2
V2	1.8-2.0	V6	2.6-2.8	V10	3.4-3.6	V14	4.2-4.4
V3	2.0-2.2	V7	2.8-3.0	V11	3.6-3.8	V15	4.4-4.6
V4	2.2-2.4	V8	3.0-3.2	V12	3.8-4.0	V16	4.6-4.8


Color ranking for white LEDs


Chromaticity Coordinates Ranks (IF=20mA Ta=25℃)


Wa1	X	0.243	0.215	0.230	0.263	Wa2	X	0.263	0.246	0.264	0.280
	Y	0.200	0.230	0.250	0.220		Y	0.220	0.236	0.267	0.248
Wa3	X	0.246	0.230	0.248	0.264	Wb1	X	0.280	0.264	0.283	0.296
	Y	0.236	0.250	0.286	0.267		Y	0.248	0.267	0.305	0.276
Wb2	X	0.264	0.248	0.275	0.283	Wc1	X	0.296	0.287	0.330	0.330
	Y	0.267	0.286	0.321	0.305		Y	0.276	0.295	0.339	0.318
Wc2	X	0.287	0.283	0.330	0.330	Wc3	X	0.283	0.275	0.298	0.306
	Y	0.295	0.305	0.360	0.339		Y	0.305	0.321	0.350	0.332
Wc4	X	0.306	0.298	0.321	0.330	Wd1	X	0.330	0.330	0.361	0.356
	Y	0.332	0.350	0.379	0.360		Y	0.318	0.360	0.385	0.351
Wd2	X	0.330	0.321	0.366	0.361	Wf	X	0.356	0.366	0.391	0.380
	Y	0.360	0.379	0.419	0.385		Y	0.351	0.419	0.436	0.381





Typical electrical/optical characteristic curves：












•SOLDERING


METHOD	SOLDERING CONDITIONS	REMARK
DIP SOLDERING	Bath temperature: 260±5℃ Immersion time: with 5 sec	• Solder no closer than 3mm from the base of the package • Using soldering flux," RESIN FLUX" is recommended.
SOLDERING IRON	Soldering iron: 30W or smaller Temperature at tip of iron: 260℃ or lower Soldering time: within 5 sec.	• During soldering, take care not to press the tip of iron against the lead. (To prevent heat from being transferred directly to the lead, hold the lead with a pair of tweezers while soldering

1) When soldering the lead of LED in a condition that the package is fixed with a panel (See Fig.1), be careful not to stress the leads with iron tip.




(Fig. 1)

2) When soldering wire to the lead, work with a Fig (See Fig.2) to avoid stressing the package.



(Fig. 2)

3) Similarly, when a jig is used to solder the LED to PC board, take care as much as possible to avoid steering the leads (See Fig.3).



(Fig.)3

4) Repositioning after soldering should be avoided as much as possible. If inevitable, be sure to preserve the soldering conditions with irons stated above: select a best-suited method that assures the least stress to the LED.
5) Lead cutting after soldering should be performed only after the LED temperature has returned to normal temperature.

•LED MOUNTING METHOD

1) When mounting the LED by using a case, as shown Fig.4, ensure that the mounting holds on the PC board match the pitch of the leads correctly-tolerance of dimensions of the respective components including the LED should be taken into account especially when designing the case, PC board, etc. to prevent pitch misalignment between the leads and board holes, the diameter of the board holes should be slightly larger than the size of the lead. Alternatively, the shape of the holes should be made oval. (See Fig.4)




Fig.4

2) Use LEDs with stand-off (Fig.5) or the tube or spacer made of resin (Fig.6) to position the LEDs.




Fig.5




Fig.6

•FORMED LEAD

1) The lead should be bent at a point located at least 2mm away from the package. Bending should be performed with base fixed means of a jig or pliers (Fig.7)




Fig. 7

2) Forming lead should be carried our prior to soldering and never during or after soldering.
3) Form the lead to ensure alignment between the leads and the hole on board, so that stress against the LED is prevented. (Fig.8)




Fig.8

•LEAD STRENGTH

1) Bend strength
   Do not bend the lead more than twice. (Fig.9)




Fig.9

2) Tensile strength (@Room Temperature)
   If the force is 1kg or less, there will be no problem. (Fig.10)



Fig.10

•HANDLING PRECAUTIONS

Although rigid against vibration, the LEDs may damaged or scratched if dropped. So take care when handling.

•CHEMICAL RESISTANCE

1) Avoid exposure to chemicals as it may attack the LED surface and cause discoloration.
2) When washing is required, refer to the following table for the proper chemical to be sued.
   (Immersion time: within 3 minutes at room temperature.)

SOLVENT	ADAPTABILITY
Freon TE	⊙
Chlorothene	╳
Isopropyl Alcohol	⊙
Thinner	╳
Acetone	╳
Trichloroethylene	╳

⊙--Usable ╳--Do not use.

NOTE: Influences of ultrasonic cleaning of the LED resin body differ depending on such factors as the oscillator output, size of the PC board and the way in which the LED is mounted.
Therefore, ultrasonic cleaning should only be performed after confirming there is no problem by conducting a test under practical.


LED LAMP PASSED TESTS

Experiment Item:


Item	Test Condition Lamp & IR	Reference Standard
OPERATION LIFE	Ta： 25±5℃ IF= 20mA RH：＜=60%RH ① DYNAMIC:100mA 1ms 1/10 duty ② STATIC STATE: IF＝20mA TEST TIME: 168HRS（-24HRS，+24HRS） 500HRS（-24HRS，+24HRS） 1000HRS（-24HRS，+72HRS）	MIL-STD-750：1026 MIL-STD-883：1005 JIS C 7021：B-1
HIGH TEMPERATURE HIGH HUMIDITY STORAGE	Ta： 65℃±5℃ RH： 90～95%RH TEST TIME：240HRS±2HRS	MIL-STD-202：103B JIS C 7021 ：B-1
TEMPERATURE CYCLING	105℃～25℃～-55℃～25℃ 30min 5min 30min 5min 10CYCLES	MIL-STD-202：107D MIL-STD-750：1051 MIL-STD-883：1010 JIS C 7021 ：A-4
THERMAL SHOCK	105℃±5℃～-55℃±5℃ 10min 10min 10CYCLES	MIL-STD-202：107D MIL-STD-750：1051 MIL-SYD-883：1011
SOLDER RESISTANCE	T，sol：260℃±5℃ DWELL TIME：10±lsec	MIL-STD-202：210A MIL-STD-750-2031 JIS C 7021：A-1
SOLDERABILITY	T，sol：230℃±5℃ DWELL TIME：5±lsec	MIL-STD-202：208D MIL-STD-750：2026 MIL-STD-883：2003 JIS C 7021 ：A-2

Drive Method

Circuit model A



Circuit model B



(A)Recommended circuit.

(B)The difference of brightness between LED`s could be found due to the Vf-If characteristics of LED.